


Mobile Origin
GaN 35W
Travel Adapter PW4
EU/UK/US/AUS
3x USB-C + 2x USB-A

PN: MO-TRA35-PW4

User Manual



www.mobileorigin.com



F



G




H



I



J



K



L



M



N




S


I.




II.



III.




IV.




V.






EU PLUG/TYPE C



US PLUG/TYPE A



AUS PLUG/TYPE I



AUS PLUG/TYPE I




Type A Type B Type C Type E Type F Type G



Type H Type I Type J Type K Type L

1.



2.



Product Description:

- A)** AC Output
- B)** LED Indicator
- C)** USB-C 3x (C1/C2/C3)
- D)** USB-A 2x (A1/A2)
- E)** Plug Control EU/UK/US/AUS

Compatible Devices:

- F)** Electric Fan
- G)** Hair Straightener
- H)** Kettle
- I)** Small Travel Hair Dryers
- J)** Electric Razor
- K)** Controller
- L)** Earbuds
- M)** Smartphone
- N)** Tablet
- S)** Camera

Specifications:

Input: 100–250V ~ 50/60Hz, 10A Max,
250V~10A/2500W, 100V~10A/1000W

Single Port Output Mode:

- A2 Output: 5V/2.4A
- C2/C3 Output: 5V/3A
- A1 Output: 5V/3A, 9V/2A, 12V/1.5A (18W Max)

C1 Output: 5V/3A, 9V/3A, 12V/2.5A, 15V/2.3A, 20V/1.75A (35W Max)

Dual Port Output Mode:

C1+A1 Output: 5V/3A (15W Max)

A2+(C2/C3) Output: 5V/3A (15W Max)

C1+A2 Output: 20W+12W (32W Max)

C1+(C2/C3) Output: 20W+15W (35W Max)

A1+A2 Output: 18W+12W (30W Max)

A1+(C2/C3) Output: 18W+15W (33W Max)

Three Port Output Mode:

A2+C2+C3 Output: 5V/3A (15W Max)

A1+(A2+C2) Output: 18W+15W (33W Max)

(C1+A1)+A2 Output: 15W+12W (27W Max)

(C1+A1)+C2/C3 Output: 15W+15W (30W Max)

C1+(A2+C2) Output: 20W+15W (35W Max)

Four Port Output Mode:

(C1+A1)+(A2+C2) Output: 15W+15W (30W Max)

A1+(A2+C2+C3) Output: 18W+15W (33W Max)

Five Port Output Mode:

(C1+A1)+(A2+C2+C3) Output: 5V/6A (30W Max)

Product Dimensions: 54 x 56 x 73 mm

Colour: Black

Material: PC

Weight: 173 g

Package Contents:

GaN 35W Travel Adapter PW4 EU/UK/US/AUS, 3x

USB-C + 2x USB-A

User Manual

Instructions For Use:

1. Socket Selection: Based on the country you're located in, **(O)** rotate the adapter (see the "rotate" image), **(P)** and select the appropriate plug type (EU, US, AUS, UK).

Only one plug-type can be used at one time, other plug-pins are locked automatically.

2. Usage Modes:

The adapter automatically switches between single-port, dual-port, three-port, and four-port modes based on the number of connected devices (see the image with modes).

3. Fuse Replacement:

1) When the travel adapter is used in conjunction with high-power devices that exceed the standard, the fuse may blow. At this time, a new main fuse needs to be replaced, all pins should be reversed,

and a screwdriver or similar item should be used to pry open the main fuse cover.

2) The main fuse can be removed together with the fuse cover, and at the same time, pry open the spare fuse cover, install the spare fuse into the main fuse cover, and reinstall it in its original position.

4. Connecting Devices:

- Plug the adapter into the socket.
- Connect your device to the corresponding port (AC Input, USB-C1/C2/C3, USB-A).

5. Warnings and Safety:

Carefully read the manual before use.

- Do not overload the adapter: The maximum power is 2500 W at 250 V.
- This adapter does NOT convert voltage. To use an AC-powered electric device abroad, Please ENSURE it supports Dual Voltage (with "100-250V, 50/60Hz" printed on it).
- The adapter is not intended for voltage conversion—check your device's compatibility.
- Do not use in wet environments or with damaged cables.
- Each country has its own regulations regarding the use of travel adapters, please check in each country before use.

- No grounding, this product is for use with unearthed or double insulated appliances only.
- Built-in safety shutters protect users from the direct touch of the parts on the socket outlet.
- Only one plug-type can be used at one time, other plug-pins are locked automatically.

Important Safety Instructions:

- DO NOT apply excessive force or subject the product to impacts.
- DO NOT disassemble, burn, or expose the product to water, whether in use or not.
- Avoid using the product in extremely high temperatures, high humidity, or dusty environments.
- Using incompatible accessories may pose a risk of injury or damage.
- The product may become warm during charging. This is a normal operating condition and not a cause for concern. If you notice an unusually high temperature, we recommend disconnecting the device from charging and allowing it to cool down before using it again.
- DO NOT clean the product with chemicals or detergents. Use a dry or slightly damp cloth instead.
- Keep the product out of reach of children and pets. This is not a toy.

Warranty does not apply in the following cases:

Damage resulting from improper transportation or unavoidable external factors such as floods, fires, lightning, earthquakes, or other natural disasters. Any damages caused by human factors, misuse of the product, unauthorised alteration to or change of parts components of the product, etc.

Note:

It is important to follow the safety precautions and instructions to avoid any risk of damage to your equipment or injury.

This product is subject to the WEEE Directive (2012/19/EU) and must not be disposed of with regular household waste. At the end of its life, please take it to an appropriate collection point for the recycling of electrical and electronic equipment.

This product complies with the requirements of the applicable EU directives and standards. Conformity assessment has been carried out in accordance with the relevant regulations.

In case of any problems or uncertainties, please contact the manufacturer at customercare@mobileorigin.com.

Popis produktu:

- A)** Vstup AC
- B)** LED indikátor
- C)** USB-C 3x (C1/C2/C3)
- D)** USB-A 2x (A1/A2)
- E)** Volba zástrčky (EU, US, AUS, UK)

Kompatibilní zařízení:

- A)** Elektrický ventilátor
- B)** Žehlička na vlasy
- C)** Rychlovarná konvice
- D)** Cestovní fén na vlasy
- E)** Elektrický holicí strojek
- F)** Herní ovladač
- G)** Sluchátka
- H)** Smartphone
- I)** Tablet
- J)** Fotoaparát

Specifikace:

Název produktu: Mobile Origin GaN 35W Cestovní adaptér PW4 EU/UK/US/AUS, 3x USB-C + 2x USB-A

Model: MO-TRA35-PW4

Vstup: 100–250V ~ 50/60Hz, 10A Max,
250V10A/1000W

Režim výstupu jednoho portu:

- Výstup A2: 5V/2.4A
- Výstup C2/C3: 5V/3A
- Výstup A1: 5V/3A, 9V/2A, 12V/1.5A (max. 18W)
- Výstup C1: 5V/3A, 9V/3A, 12V/2.5A, 15V/2.3A, 20V/1.75A (max. 35W)

Režim výstupu dvou portů:

- C1 + A1: 5V/3A (max. 15W)
- A2 + (C2/C3): 5V/3A (max. 15W)
- C1 + A2: 20W + 12W (max. 32W)
- C1 + (C2/C3): 20W + 15W (max. 35W)
- A1 + A2: 18W + 12W (max. 30W)
- A1 + (C2/C3): 18W + 15W (max. 33W)

Režim výstupu tří portů:

- A2 + C2 + C3: 5V/3A (max. 15W)
- A1 + (A2 + C2): 18W + 15W (max. 33W)
- (C1 + A1) + A2: 15W + 12W (max. 27W)
- (C1 + A1) + C2/C3: 15W + 15W (max. 30W)
- C1 + (A2 + C2): 20W + 15W (max. 35W)

Režim výstupu čtyř portů:

- (C1 + A1) + (A2 + C2): 15W + 15W (max. 30W)
- A1 + (A2 + C2 + C3): 18W + 15W (max. 33W)

Režim výstupu pěti portů:

- (C1 + A1) + (A2 + C2 + C3): 5V/6A (max. 30W)

Rozměry produktu: 54 x 56 x 73 mm

Barva: Černá

Materiál: PC (polykarbonát)

Hmotnost: 173 g

Obsah balení:

- GaN 35W Cestovní adaptér PW4 EU/UK/US/AUS, 3x USB-C + 2x USB-A
- Uživatelský manuál

Návod k použití:

1. Volba zásuvky:

V závislosti na zemi, ve které se nacházíte, **(O)** Otočte adaptérem (viz obrázek „otočení“), **(P)** a vyberte odpovídající typ zástrčky (EU, US, AUS, UK).

Lze použít pouze jeden typ zástrčky najednou, ostatní kolíky jsou automaticky uzamčeny.

2. Připojení zařízení:

- Zasuňte adaptér do zásuvky.
- Připojte své zařízení k odpovídajícímu portu (AC vstup, USB-C1/C2/C3, USB-A).

3. Režimy použití:

Adaptér se automaticky přepíná mezi režimy podle počtu připojených zařízení (viz obrázek s režimy).

4. Výměna pojistky:

1. Při používání s výkonnými zařízeními může pojistka vyhořet. V takovém případě je nutné vyměnit hlavní pojistku – všechny kolíky otočte zpět, a pomocí šroubováku nebo podobného nástroje

otevřete kryt hlavní pojistky.

2. Hlavní pojistku lze vyjmout společně s krytem, zároveň otevřete kryt náhradní pojistky, vložte náhradní pojistku do krytu hlavní pojistky a vraťte ji zpět na původní místo.

Upozornění a bezpečnostní pokyny:

Před použitím si pečlivě přečtete návod.

- Nepřetěžujte adaptér: Maximální výkon je 2500 W při 250 V.
- Tento adaptér NEPŘEVÁDÍ napětí. Při použití AC zařízení v zahraničí SE UJISTĚTE, že podporuje duální napětí (s údajem "100-250V, 50/60Hz").
- Adaptér není určen pro změnu napětí – zkontrolujte kompatibilitu zařízení.
- Nepoužívejte ve vlhkém prostředí ani s poškozenými kabely.
- Každá země má vlastní předpisy týkající se používání cestovních adaptérů – před použitím je zkontrolujte.
- Bez uzemnění – produkt je určen pouze pro zařízení s dvojitou izolací nebo bez nutnosti uzemnění.
- Vestavěné bezpečnostní clony chrání uživatele před přímým dotykem části zásuvky.
- Lze použít pouze jeden typ zástrčky najednou – ostatní kolíky se automaticky uzamykají.

Důležité bezpečnostní pokyny:

- NEPOUŽÍVEJTE nadměrnou sílu, ani nevystavujte produkt nárazům.
- NEDEMONTUJTE, nespalujte ani nevystavujte vodě.
- Vyhněte se použití ve vysokých teplotách, vlhkosti nebo prašném prostředí.
- Používání nekompatibilního příslušenství může vést k poškození nebo úrazu.
- Produkt se může během nabíjení zahřívat – to je běžný jev. Pokud dojde k přehřátí, odpojte zařízení a nechte adaptér vychladnout.
- NEČISTĚTE chemikáliemi nebo saponáty – použijte suchý nebo mírně navlhčený hadřík.
- Uchovávejte mimo dosah dětí a zvířat – nejedná se o hračku.

Záruka se nevztahuje na případy:

- Poškození v důsledku nesprávné přepravy nebo nevyhnutelných vnějších faktorů (povodně, požár, blesk, zemětřesení apod.).
- Jakékoli poškození způsobené lidským faktorem, nesprávným použitím, neautorizovanou úpravou či výměnou částí produktu atd.

Poznámka:

Je důležité dodržovat bezpečnostní pokyny a instrukce, aby nedošlo k poškození zařízení nebo úrazu.

Tento produkt podléhá směrnici WEEE (2012/19/EU) a nesmí být likvidován společně s běžným odpadem. Po skončení životnosti jej odevzdejte ve sběrném místě pro elektroodpad.

Tento produkt splňuje požadavky příslušných směrnic a norem EU. Posouzení shody bylo provedeno v souladu s platnými předpisy.

V případě problémů nebo nejasností kontaktujte výrobce na: customercare@mobileorigin.com

Mobile Origin



Producer: S-Cube s.r.o.

Email: customercare@mobileorigin.com

www.mobileorigin.com

Address: Krajankova 3176/2,
Prague, 141 00, Czechia

Made in China

www.mobileorigin.com



RoHS